


- 1. See Standard Plan J-21.10 for Ramp Meter Signal Standard and Foundation Details.
- 2. See Standard Specification 9-29.17 for additional Mounting Bracket and Fitting information not shown.
- 3. Top of Leveling Nut height shall be 1" (in) max. above foundation.
- 4. Heat-shrink cap for all spare conductors not terminated on a terminal strip.
- 5. Provide Cable Tie at wiring entering the Junction Box (Slip Base installations only). See Detail A, Standard Plan J-28.70.




(в)

C

**PERSPECTIVE VIEW** 

**RAMP METER** 

COLOR	USE
R	RED DISPLAY
0	AMBER DISPLAY
G	GREEN DISPLAY
w	NEUTRAL CONDUCTOR
В	SPARE CONDUCTOR



**RAMP METER SIGNAL STANDARD ELECTRICAL DETAILS** 

**STANDARD PLAN J-22.16-03** 

SHEET 1 OF 1 SHEET

APPROVED FOR PUBLICATION

STATE DESIGN ENGINEER